



**LOAD TABULATION FOR LIGHTING CONTROLLER "WK" BEMES ROAD**

CIRCUIT	DESCRIPTION	PHASE A (RED) AMPS	PHASE B (BLACK) AMPS	BREAKER SIZE AMPS
A	(2) FIXT @ 1.94A, (5) NEW FIXT @ 1.53A	11.53 (13.58)		70A, 1 POLE
B	(1) EX FIXT @ 1.94A, (6) NEW FIXT @ 1.53A		9.59 (9.18)	70A, 1 POLE
C	(2) EX FIXT @ 1.94A, (5) NEW FIXT @ 1.53A	11.53 (13.58)		70A, 1 POLE
D	(2) EX FIXT @ 1.94A, (5) NEW FIXT @ 1.53A		11.53 (13.58)	70A, 1 POLE
E	(3) EX FIXT @ 1.94A, (1) NEW FIXT @ 1.53A	7.35 (7.76)		70A, 1 POLE
F	(2) EX FIXT @ 1.94A, (1) NEW FIXT @ 1.53A		5.41 (5.82)	70A, 1 POLE
G	(2) FIXT @ 1.94A, (1) NEW FIXT @ 1.53A	5.41 (7.76)		70A, 1 POLE
H	(3) FIXT @ 1.94A, (1) NEW FIXT @ 1.53A		7.35 (7.76)	70A, 1 POLE
TOTAL CONNECTED LOAD @ 240V, 1 PH.		35.82A (42.68A)	33.88A (36.34A)	
TOTAL CONNECTED LOAD @ 240V, 1 PH.		8.6KVA (10.2KVA)	8.13KVA (8.7KVA)	
TOTAL CONNECTED LOAD @ 480V, 1 PH.		34.9A (39.38A)		

NOTE: AMPERAGE IN PARENTHESIS REPRESENT FUTURE LUMINARIES WITH A 400W HPS LAMPS.

**LEGEND**

- PROPOSED 310W HPS LUMINAIRE
- PROPOSED 310W HPS LUMINAIRE
- PROPOSED LIGHTING CONTROLLER, SINGLE TYPE
- B BLACK PHASE CONDUCTOR
- W WHITE NEUTRAL CONDUCTOR
- R RED PHASE CONDUCTOR
- G GREEN GROUND CONDUCTOR

**NOTE:**

1. SEE TRAFFIC PLANS FOR STATIONS.



L:\Jobs\2006\20063028-39\CAD\Electrical\dgn\00\E23.cad 12/28/2007 10:51:35 AM