F.A. RTE.	SECTION	COUNTY	TOTAL SHEETS	SHEET NO.
	03-00026-00-PK	MADISON	38	38

FEDERAL AID PROJECT

PANELBOARD - **LP** VOLTAGE 208 / 120 AMP BUS - SPECIAL FEATURES -
MOUNTING - SURFACE PHASE 3 AMP MCB 100
A.I.C. RATING - 22,000 WIRE 4 AMP M.L.O. 100

LOAD DESCRIPTION	LOAD (VA) LIGHT	RECEP.	HVAC	MISC.	BREAKER AMP	POLES	CIRCUIT	3 PH. A	B	C	CIRCUIT	BREAKER POLES	AMP	LOAD (VA) LIGHT	RECEP.	HVAC	MISC.	LOAD DESCRIPTION
NW FLOODLIGHT	1650				20*	2	1				2	1	20	912				EXTERIOR ENTRY LIGHTING
	1650						3				4	1	20*	742				EXTERIOR ENTRY LIGHTING
SW FLOODLIGHT	1650				20*	2	5				6	1	20	925				PLAZA LIGHTING SOUTH
	1650						7				8	1	20	925				PLAZA LIGHTING NORTH
SE FLOODLIGHT	1650				20*	2	9				10	1	20*	1000				FOUNTAIN LIGHTING
	1650						11				12	2	20	500				PARKING LOT LIGHTING NORTH
NE FLOODLIGHT	1650				20*	2	13				14			500				
	1650						15				16	1	20	1000				WATER WALL FLOODLIGHTS
PARKING LOT LIGHTING NORTH	1500				20	2	17				18	1	20	1000				WATER WALL FLOODLIGHTS
	1500						19				20	1	20	1000				WATER WALL FLOODLIGHTS
PARKING LOT LIGHTING SOUTH	750				20*	2	21				22	1	20	1000				WATER WALL FLOODLIGHTS
	750						23				24	1	20					SPARE
PARKING LOT LIGHTING SOUTH	750				20*	2	25				26	1	20					SPARE
	750						27				28	1	20					SPARE
SPARE					20	1	29				30	1	20					SPARE
SPARE					20	1	31				32	1	20					SPARE
SPARE					20	1	33				34	1	20					SPARE
SPARE					20	1	35				36	1	20					SPARE
SPARE					20	1	37				38	1	20					SPARE
SPARE					20	1	39				40	1	20					SPARE
CONTACTORS C1 AND C2	100				20	1	41				42	1	20					SPARE

NOTES: ALL CIRCUIT BREAKERS SHOWN IN THIS PANEL SCHEDULE SHALL BE PROVIDED WITH THIS PANEL UNDER THE PHASE 2B CONTRACT. THE LOAD IDENTIFIED AT BREAKERS WITH AN ASTERISK (*) BEHIND THE AMPERAGE VALUE SHALL BE CONNECTED TO THIS PANEL AS PART OF THE PHASE 2A CONTRACT.

PANELBOARD - **LRPS** VOLTAGE 208 / 120 AMP BUS 200 SPECIAL FEATURES -
MOUNTING - SURFACE PHASE 3 AMP MCB -
A.I.C. RATING - 22,000 WIRE 4 AMP M.L.O. 200

LOAD DESCRIPTION	LOAD (VA) LIGHT	RECEP.	HVAC	MISC.	BREAKER AMP	POLES	CIRCUIT	3 PH. A	B	C	CIRCUIT	BREAKER POLES	AMP	LOAD (VA) LIGHT	RECEP.	HVAC	MISC.	LOAD DESCRIPTION
LIGHTING	770				20	1	1				2	1	20		1000			RECEPTACLES
			2000				3				4	1	20			900		EF-2 AND DAMPER
CABINET UNIT HEATER CUH-2			2000		25	3	5				6	1	20					SPARE
			2000				7				8					1100		UNIT HEATER UH-2
			2000				9				10	3	20			1100		
CABINET UNIT HEATER CUH-1			2000		25	3	11				12					1100		
			2000				13				14	1	20		2300			HAND DRYER
				3276			15				16	1	20		2300			HAND DRYER
FOUNTAIN PUMPS FP-1 & FP-2				3276	40*	3	17				18	1	20			400		MOTORIZED DAMPER B
				3276			19				20	1	20		1400			RECEPTACLES
MOTORIZED DAMPER				1000	20*	1	21				22	1	20		2300			HAND DRYER
RECEPTACLES		800			20*	1	23				24	1	20		2300			HAND DRYER
SPARE					20	1	25				26					3333		
SPARE					20	1	27				28	3	40*			3333		UNIT HEATER UH-1
SPARE					20	1	29				30					3333		
PLATFORM RECEPTACLES		600			20*	1	31				32	1	20		1000			RECEPTACLE - FOOD WARMING
LIFE SAFETY LIGHTING	360				20**	1	33				34	1	20		200			RECEPTACLE AT PODIUM
FIRE ALARM CONTROL PANEL				1000	20**	1	35				36	1	20				5000	
AV APPLIANCE PWR. SUPPLY				1000	20**	1	37				38	1	20				3000	WATER HEATER WH-1
SPARE					20	1	39				40	1	20				3000	
FOUNTAIN CONTROL PANEL				500	20*	1	41				42	1	20					SPARE
SPARE					20	1	43				44	1	20					SPARE
SPARE					20	1	45				46	1	20					SPARE
SPARE					20	1	47				48	1	20					SPARE
SPARE					20	1	49				50	1	20					SPARE
SPARE					20	1	51				52	1	20					SPARE
SPARE					20	1	53				54	1	20					SPARE
SPARE					20	1	55				56	1	20					SPARE
SPARE					20	1	57				58	1	20					SPARE
SPARE					20	1	59				60	1	20					SPARE
SPARE					20	1	61				62	1	20					SPARE
SPARE					20	1	63				64	1	20					SPARE
SPARE					20	1	65				66	1	20					SPARE
SPARE					20	1	67				68	1	20					SPARE
SPARE					20	1	69				70	1	20					SPARE
SPARE					20	1	71				72	1	20					SPARE
SPARE					20	1	73				74	1	20					SPARE
SPARE					20	1	75				76	1	20					SPARE
SPARE					20	1	77				78	1	20					SPARE
SPARE					20	1	79				80	1	20					SPARE
SPARE					20	1	81				82	1	20					SPARE
SPARE					20	1	83				84	1	20					SPARE

NOTES: ALL CIRCUIT BREAKER SHOWN IN THIS SCHEDULE SHALL BE PROVIDED UNDER THE PHASE 2B CONTRACT. WHERE A SINGLE ASTERISK APPEARS BY THE AMPERAGE VALUE OF A BREAKER, THE LOAD IDENTIFIED FOR THAT BREAKER SHALL BE CONNECTED TO THIS PANEL AS PART OF THE PHASE 2A CONTRACT. CIRCUIT BREAKERS WITH A DOUBLE ASTERISK (**) BEHIND THE AMPERAGE VALUE SHALL SERVE THE LOAD IDENTIFIED UNDER THE PHASE 2B CONTRACT AND SHALL BE RELABELED TO READ "SPARE" UNDER THE PHASE 2A CONTRACT.

EQUIPMENT DATA SCHEDULE

LINE NO.	MARK	EQUIPMENT DESCRIPTION	EQUIPMENT LOCATION	FURN. BY (DIV.)	MOTOR OR EQUIPMENT DATA ① HP/KW	VOLTS/ PHASE	FLA	INST. BY	CONN. BY	DISCONNECT SWITCH AT EQUIPMENT ② TYPE	FURN. BY	INST. BY	CONN. BY	STARTER ③ TYPE	FURN. BY	INST. BY	CONN. BY	REMOTE CONTROLS ④ TYPE	FURN. BY	INST. BY	CONN. BY	⑤ REMARKS
1	CUH-1	CABINET UNIT HEATER	WOMEN'S RESTROOM	15	6 KW	208/3	17.6	15	16	CB	15	FAC	16	–	–	–	–	–	–	–	–	–
2	CUH-2	CABINET UNIT HEATER	MEN'S RESTROOM	15	6 KW	208/3	17.6	15	16	CB	15	FAC	16	–	–	–	–	–	–	–	–	–
3																						
4																						
5																						
6																						
7																						
8																						
9	EF-2	EXHAUST FAN	TOILET ROOMS	15	1/4 HP	120/1	–	15	16	NF	15	FAC	16	–	–	–	–	TC	16	16	16	–
10																						
11																						
12																						
13																						
14																						
15																						
16																						
17																						
18																						
19																						
20																						
21																						
22																						
23	WH-1	WATER HEATER	–	15	1.5 KW	120/1	–	15	16	S	16	16	16	–	–	–	–	–	–	–	–	
24																						
25																						
26																						
27																						
28																						
29																						
30																						
31																						
32																						
33																						
34																						
35																						
36																						
37																						
38																						
39																						
40																						

① HORSEPOWER (HP) IS SHOWN UNLESS KILLOWATTS (KW) ARE CALLED OUT.

② DISCONNECT TYPES:
CB = CIRCUIT BREAKER
F = FUSED
NF = NON FUSED
S = SWITCH (TOGGLE)
WP = WEATHERPROOF
FAC = FACTORY

③ STARTER TYPES:
COMB = COMBINATION MAGNETIC FVNR WITH FUSIBLE DISCONNECT SWITCH
FVNR = FULL VOLTAGE NON-REVERSING
MAN = MANUAL STARTER
PWCP = PRE-WIRED CONTROL PANEL WITH INTEGRAL FVNR MAGNETIC STARTER AND DISCONNECT SWITCH
SDS = STAR DELTA STARTER
VSD = VARIABLE SPEED DRIVE
2S2W = 2 SPEED, 2 WINDING MAGNETIC STARTER

④ REMOTE CONTROL:
BAS = BUILDING AUTOMATION SYSTEM
FAI = FIRE ALARM INTERLOCK
FST = FIRESTAT
INT = INTERLOCK WITH OTHER EQUIPMENT
RAD = REMOTE ALARM DEVICE
RPB = REMOTE START-STOP PUSH BUTTON
SSC = START-STOP CONTACT
TC = TIME CLOCK
TS = THERMOSTAT

⑤ REMARKS:
1. EMERGENCY POWER.
2. 2 SPEED, 2 WINDING MOTOR.
3. STAND-BY UNIT.
4. VARIABLE SPEED DRIVE WITH PRE-WIRED STARTER AND INTEGRAL DISCONNECT SWITCH.

KAI
211 N. Broadway
Suite 1600
St. Louis, MO
63102
(314) 241-9100
FAX (314) 241-9125

PHASE 2B
LEWIS AND CLARK MEMORIAL TOWER
VILLAGE OF HARTFORD, ILLINOIS
HARTFORD, ILLINOIS 62049

SHEET TITLE:
EQUIPMENT DATA SCHEDULE

REV. NO.	REMARKS	DATE

KENNEDY PROJECT NO
KAI# 10-02048

ISSUE DATE
12-JULY-05

SHEET NO
E7-02

©2005 KENNEDY ASSOCIATES INCORPORATED

P:\2002\10-02048\600DGS\E287 02.DWG | 12/1/2005 5:10:19 PM | Xref's: TS24J60DL | Images: none