

21st & Marshall Ave.

LOOP:	SIZE:	MODE:	QUADRA-POLE:	DELAY:
A1,A4,A6,A2,A5,A7, C1,C3,C5,C2,C4,C6	6' X 6'	NORMAL	NO	0
A8,C7	6' X 6'	EXTENDED	NO	0
A3	6' X 6'	DELAY	NO	15

THE FOLLOWING CABLES SHALL BE WIRED TO COMMON AMPLIFIERS:
(A1,A4,A6), (A2,A5,A7),(A3), (A8),
(C1,C3,C5), (C2,C4,C6), (C7)
7 AMPLIFIERS PLUS 3 ADDITIONAL
TOTAL 10 AMPLIFIERS

STATION EQUATION
STATION 72+30.40 (MARSHALL AVE.) =
STATION 72+30.40 (21ST ST. NORTH) =
STATION 10+00 (21ST ST. SOUTH) =
STATION 0+00 (MARSHALL AVE. EAST OF 21ST ST.)

NUMBER OF TURNS REQUIRED

6 X 6		LOOP SIZE
		2 TURNS
		3 TURNS
0	545	4 TURNS
546	818	5 TURNS
819	1145	6 TURNS
1146	1527	7 TURNS
1528	1964	8 TURNS
1965	2455	9 TURNS
2456	3000	10 TURNS

THE NUMBERS IN THE TABLE REPRESENT THE LENGTH OF ELECTRIC CABLE FROM THE LOOP TO THE CABINET

