ELECTRICAL SCHEDULE

DESCRIPTION	STATION	LT/RT	CENTER LINE SETBACK	FIXTURE TYPE	COMMENT
WEST MAIN STREET					
POWER PLUG PL2-1 POINT 1	28+51-3"	LT	24'-9½"		–
POWER PLUG PL2-1 POINT 2	28+53-8½"	LT	24'-9½"		–
POWER PLUG PL3-1 POINT 1	28+51-3"	RT	2'-4½"		–
POWER PLUG PL3-1 POINT 2	28+53-8½"	RT	2'-4½"		–
STREET LIGHT	28+71-2½"	LT	26'-5"	B	–
STREET LIGHT	28+71-2½"	RT	26'-5"	B	–
PLAZA LIGHT	27+28-11"	LT	26'-5"	B	–
STREET LIGHT	27+21-2½"	RT	26'-5"	B	–
PLAZA LIGHT	27+69-3½"	LT1	43'-7"	C	NEW FIXTURE. RE-USE EXISTING BASE AND WIRING.
PLAZA LIGHT	27+69-3½"	LT2	55'-2"	C	NEW FIXTURE. RE-USE EXISTING BASE AND WIRING.
PLAZA LIGHT	28+12-3½"	LT1	43'-7"	C	NEW FIXTURE. RE-USE EXISTING BASE AND WIRING.
PLAZA LIGHT	28+12-3½"	LT2	55'-2"	C	NEW FIXTURE. RE-USE EXISTING BASE AND WIRING.
STREET LIGHT	27+90-2"	LT	26'-4"	B	–
STREET LIGHT	27+71-2½"	RT	26'-5½"	B	–
INGROUND FLAGPOLE LIGHT	27+80-6½"	LT1	84'-3"	EXT	FIXTURE TO REMAIN.
INGROUND FLAGPOLE LIGHT	27+80-6½"	LT2	97'-8"	EXT	FIXTURE TO REMAIN.
BOLLARD LIGHT	27+80-10"	LT3	85'-7"	EXT	FIXTURE TO REMAIN.
BOLLARD LIGHT	27+80-10"	LT4	113'-10½"	EXT	FIXTURE TO REMAIN.
INGROUND FLAGPOLE LIGHT	27+90-7½"	LT1	84'-3"	EXT	FIXTURE TO REMAIN.
INGROUND FLAGPOLE LIGHT	27+90-7½"	LT2	97'-8"	EXT	FIXTURE TO REMAIN.
BOLLARD LIGHT	27+99-6"	LT1	85'-7"	EXT	FIXTURE TO REMAIN.
BOLLARD LIGHT	27+99-6"	LT2	113'-10½"	EXT	FIXTURE TO REMAIN.
INGROUND FLAGPOLE LIGHT	28+00-8"	LT1	84'-3"	EXT	FIXTURE TO REMAIN.
INGROUND FLAGPOLE LIGHT	28+00-8"	LT2	97'-8"	EXT	FIXTURE TO REMAIN.
STREET LIGHT	28+44-4"	LT	26'-4"	B	–
STREET LIGHT	28+23-11"	RT	26'-5"	B	–
PLAZA LIGHT	28+30-9½"	LT1	43'-8"	C	–
PLAZA LIGHT	28+30-9½"	LT2	69'-8"	C	–
PLAZA LIGHT	28+30-9½"	LT3	100'-8"	C	–
PLAZA LIGHT	28+30-9½"	LT4	122'-0"	C	–
PLAZA LIGHT	28+46-11"	RT1	47'-8"	C	–
PLAZA LIGHT	28+46-11"	RT2	65'-8"	C	–
POWER PLUG PL3-2 POINT 1	28+47-5½"	RT	35'-0½"		–
POWER PLUG PL3-2 POINT 2	28+48-10½"	RT	35'-0½"		–
PLAZA LIGHT	28+50-3"	RT	65'-8"	C	–
POWER PLUG PL2-2 POINT 1	28+50-6½"	LT	27'-1½"		–
PLAZA LIGHT	28+52-10½"	LT1	58'-11"	C	–
PLAZA LIGHT	28+52-10½"	LT2	122'-0"	C	–
POWER PLUG PL2-3 POINT 1	28+53-0"	LT	112'-10½"		–
POWER PLUG PL2-2 POINT 2	28+53-1½"	LT	27'-11½"		–
POWER PLUG PL2-3 POINT 2	28+54'-7"	LT	112'-10½"		–
INGROUND ART LIGHT	28+52-0"	LT	86'-3"	D	–
INGROUND ART LIGHT	28+54-8½"	LT1	60'-11"	D	–
INGROUND ART LIGHT	28+54-8½"	LT2	70'-9½"	D	–
INGROUND ART LIGHT	28+54-5"	LT3	94'-0"	D	–
PLAZA LIGHT	28+85-6½"	RT	97'-10"	C	–
INGROUND ART LIGHT	28+54-5"	LT	86'-3"	D	–
STREET LIGHT	28+75-10"	LT	37'-3½"	AA	PROVIDE WITH YIELD SIGN.
STREET LIGHT	28+78'-3"	RT	38'-0½"	AB	–
INGROUND ART LIGHT	28+77-10½"	LT	90'-9½"	D	–
INGROUND ART LIGHT	28+80-11½"	LT	90'-9½"	D	–
PLAZA LIGHT	28+83-4½"	LT	106'-10½"	C	–
PLAZA LIGHT	28+84-10½"	LT	122'-0"	C	–
PLAZA LIGHT	28+99-10½"	LT	99'-10"	C	–
PLAZA LIGHT	28+90-4"	RT	104'-11"	C	–
STREET LIGHT	28+16-2"	LT	75'-10½"	AA	–
STREET LIGHT	29+17-7"	RT	76'-3½"	AB	PROVIDE WITH YIELD SIGN.
PLAZA LIGHT	29+18-4"	RT	104'-11"	C	–
PLAZA LIGHT	29+19'-10"	LT	122'-0"	C	–
SOUTH ILLINOIS STREET					
POWER PLUG PL8-1 POINT 1	46+13-0"	RT	23'-8½"		–
POWER PLUG PL8-1 POINT 2	46+15-6"	RT	23'-8½"		–
STREET LIGHT	46+17-0"	LT	27'-2"	B	–
STREET LIGHT	46+18'-1"	RT	24'-3"	B	–
POWER PLUG PL8-3 POINT 1	46+21-0"	LT	25'-5"		–
POWER PLUG PL8-3 POINT 2	46+23-5"	LT	25'-5"		–
STREET LIGHT	46+68-0"	LT	25'-11"	B	–
STREET LIGHT	46+74'-7½"	RT	24'-8½"	B	–
POWER PLUG PL8-4 POINT 1	46+69'-0"	LT	41'-0"		–
POWER PLUG PL8-4 POINT 2	46+71'-6"	LT	41'-0"		–
STREET LIGHT	47+36'-6"	LT	26'-8"	B	–
STREET LIGHT	47+37'-1"	RT	24'-5"	B	–
STREET LIGHT	47+82'-0"	LT	26'-8"	B	–
STREET LIGHT	47+81'-1"	RT	25'-2"	B	–
POWER PLUG PL8-2 POINT 1	46+8'-8½"	RT	27'-11"		–
POWER PLUG PL3-1 POINT 1	46+8'-11"	LT	27'-0½"		–
POWER PLUG PL3-1 POINT 2	46+11'-0"	LT	26'-11½"		–
STREET LIGHT	48+9'-2"	LT	27'-3"	B	–
POWER PLUG PL3-3 POINT 2	48+11'-10"	LT	26'-0"		–
POWER PLUG PL8-3 POINT 1	46+21'-0"	LT	25'-5"		–
POWER PLUG PL8-3 POINT 2	46+23'-5"	LT	25'-5"		–
STREET LIGHT	46+68'-0"	LT	25'-11"	B	–
STREET LIGHT	46+74'-7½"	RT	24'-8½"	B	–
POWER PLUG PL8-4 POINT 1	46+69'-0"	LT	41'-0"		–
POWER PLUG PL8-4 POINT 2	46+71'-6"	LT	41'-0"		–
STREET LIGHT	47+36'-6"	LT	26'-8"	B	–
STREET LIGHT	47+37'-1"	RT	24'-5"	B	–
STREET LIGHT	47+82'-0"	LT	26'-8"	B	–
STREET LIGHT	47+81'-1"	RT	25'-2"	B	–
POWER PLUG PL8-2 POINT 1	46+8'-8½"	RT	27'-11"		–
POWER PLUG PL3-1 POINT 1	46+8'-11"	LT	27'-0½"		–
POWER PLUG PL3-1 POINT 2	46+11'-0"	LT	26'-11½"		–
STREET LIGHT	48+9'-2"	LT	27'-3"	B	–
POWER PLUG PL3-3 POINT 2	48+11'-10"	LT	26'-0"		–

DESCRIPTION	STATION	LT/RT	CENTER LINE SETBACK	FIXTURE TYPE	COMMENT
NORTH ILLINOIS STREET					
POWER PLUG PL5-2 POINT 1	50+29'-9"	RT	28'-0½"		–
POWER PLUG PL5-1 POINT 1	50+30'-5½"	LT	28'-0½"		–
POWER PLUG PL5-1 POINT 2	50+31'-11"	LT	27'-5"		–
POWER PLUG PL5-2 POINT 2	50+30'-2"	RT	27'-0½"		–
TRAFFIC SIGNAL PB POINT 1	50+44'-10"	RT	28'-0½"		–
TRAFFIC SIGNAL PB POINT 2	50+42'-10"	RT	28'-0½"		–
STREET LIGHT	50+54'-3"	LT	26'-5"	B	–
STREET LIGHT	50+88'-8"	RT	24'-0½"	B	–
STREET LIGHT	51+22'-2"	LT	26'-0½"	B	–
STREET LIGHT	51+59'-8"	RT	24'-6½"	B	–
POWER PLUG PL5-4 POINT 1	51+35'-0"	LT	25'-10"		–
POWER PLUG PL5-3 POINT 1	51+35'-0"	RT	24'-2"		–
POWER PLUG PL5-4 POINT 2	51+37'-6"	LT	25'-10"		–
POWER PLUG PL5-3 POINT 2	51+37'-8"	RT	24'-2"		–
STREET LIGHT	51+79'-3"	LT	26'-2"	B	–
STREET LIGHT	51+91'-3"	RT	24'-6½"	B	–
STREET LIGHT	52+35'-7"	LT	26'-0½"	B	–
STREET LIGHT	52+76'-7"	RT	24'-0½"	B	–
EAST MAIN STREET					
STREET LIGHT	29+92'-10½"	LT	26'-2"	B	–
PLAZA LIGHT	30+09'-0"	LT	122'-0"	C	PROVIDE POLE BASE WITH SPREAD FOOTING.
PLAZA LIGHT	30+10'-0"	RT	122'-10"	C	–
STREET LIGHT	30+13'-11"	LT	78'-3½"	AA	PROVIDE POLE BASE WITH SPREAD FOOTING.
STREET LIGHT	30+13'-11"	RT	74'-4½"	AA	–
INGROUND MONUMENT LIGHT	30+37'-0"	LT	84'-3"	D	–
INGROUND MONUMENT LIGHT	30+36'-0"	RT	130'-1"	D	–
INGROUND MONUMENT LIGHT	30+39'-0"	LT	84'-3"	D	–
INGROUND MONUMENT LIGHT	30+40'-0"	RT	130'-1"	D	–
PLAZA LIGHT	30+40'-0"	LT1	100'-8½"	C	PROVIDE POLE BASE WITH SPREAD FOOTING.
PLAZA LIGHT	30+40'-0"	LT2	122'-0"	C	PROVIDE POLE BASE WITH SPREAD FOOTING.
PLAZA LIGHT	30+40'-0"	RT1	90'-8"	C	–
PLAZA LIGHT	30+40'-0"	RT2	122'-10"	C	–
INGROUND MONUMENT LIGHT	30+51'-2½"	LT	89'-1"	D	–
INGROUND MONUMENT LIGHT	30+52'-5"	R12	94'-7"	D	–
INGROUND MONUMENT LIGHT	30+52'-5"	RT1	85'-0"	D	–
STREET LIGHT	30+52'-10½"	LT	38'-6"	AA	PROVIDE POLE BASE WITH SPREAD FOOTING AND YIELD SIGN.
STREET LIGHT	30+41'-8"	RT	74'-4½"	AA	–
INGROUND FLAG POLE LIGHT	30+55'-5½"	R11	91'-5½"	E	–
INGROUND MONUMENT LIGHT	30+56'-7"	R12	98'-2"	D	–
INGROUND MONUMENT LIGHT	30+56'-3½"	RT	81'-9"	D	–
INGROUND MONUMENT LIGHT	30+60'-3"	RT	99'-8"	D	–
INGROUND MONUMENT LIGHT	30+51'-2"	RT	80'-1"	D	–
INGROUND FLAG POLE LIGHT	30+62'-4"	RT	85'-0"	E	–
INGROUND FLAG POLE LIGHT	30+64'-7½"	RT	83'-10½"	E	–
PLAZA LIGHT	30+65'-0"	RT1	98'-10½"	D	–
PLAZA LIGHT	30+68'-2"	R12	92'-10"	D	–
INGROUND MONUMENT LIGHT	30+69'-1½"	R11	85'-0½"	D	–
INGROUND MONUMENT LIGHT	30+68'-8½"	R12	85'-3½"	D	–
INGROUND MONUMENT LIGHT	30+70'-0"	RT	99'-7"	D	–
POWER PLUG PL6-4 POINT 1	30+74'-0"	RT	102'-8"		–
POWER PLUG PL6-4 POINT 2	30+76'-8"	RT	102'-8"		–
PLAZA LIGHT	30+77'-0"	LT1	71'-8½"	C	PROVIDE POLE BASE WITH SPREAD FOOTING.
PLAZA LIGHT	30+77'-0"	LT2	122'-0"	C	PROVIDE POLE BASE WITH SPREAD FOOTING.
PLAZA LIGHT	30+77'-0"	RT	122'-10"	C	–
POWER PLUG PL6-2 POINT 1	30+82'-11½"	LT	25'-0½"		–
POWER PLUG PL6-3 POINT 1	30+83'-8"	RT	25'-10½"		–
POWER PLUG PL6-1 POINT 1	30+85'-8"	LT	114'-4"		–
POWER PLUG PL6-3 POINT 2	30+86'-0"	RT	25'-6"		–
POWER PLUG PL6-1 POINT 2	30+88'-0"	LT	116'-4"		–
STREET LIGHT	30+88'-2"	RT	25'-11"	B	–
PLAZA LIGHT	30+95'-0"	LT	97'-3"	C	PROVIDE POLE BASE WITH SPREAD FOOTING.
PLAZA LIGHT	30+95'-0"	LT1	71'-8½"	C	PROVIDE POLE BASE WITH SPREAD FOOTING.
PLAZA LIGHT	30+95'-0"	LT3	100'-8½"	C	PROVIDE POLE BASE WITH SPREAD FOOTING.
PLAZA LIGHT	30+95'-0"	LT4	122'-0"	C	PROVIDE POLE BASE WITH SPREAD FOOTING.
PLAZA LIGHT	30+95'-0"	RT1	42'-10½"	C	–
PLAZA LIGHT	30+95'-0"	RT2	69'-0"	C	–
PLAZA LIGHT	30+95'-0"	RT3	101'-8½"	C	–
PLAZA LIGHT	30+95'-0"	RT4	122'-10"	C	–
STREET LIGHT	31+12'-0½"	LT	22'-7½"	B	–
STREET LIGHT	31+43'-9"	RT	22'-11"	B	–
STREET LIGHT	31+59'-3"	LT	22'-7½"	B	–
STREET LIGHT	31+94'-8"	RT	22'-11½"	B	–
STREET LIGHT	32+9'-5"	LT	22'-7½"	B	–
STREET LIGHT	32+54'-3"	RT	22'-11½"	B	–
STREET LIGHT	32+57'-5"	LT	22'-7½"	B	–
POWER PLUG PL10-1 POINT 1	32+63'-0"	LT	21'-1"		–
POWER PLUG PL6-1 POINT 1	32+63'-0"	RT	20'-11½"		–
POWER PLUG PL10-1 POINT 2	32+65'-6"	LT	21'-1"		–
POWER PLUG PL6-1 POINT 2	32+65'-6"	RT	20'-11½"		–

LIGHT FIXTURE SCHEDULE

TYPE	MANUFACTURER & CATALOG No.	VOLTAGE	LAMPS	MOUNTING	DESCRIPTION & REMARKS
AA	STERNBERG 2-1527R/FG/CAS6-HS-LS/250MHMULTI/RO4 69251TP8/SVO/FHD/BCC/1521/FG/480PM/HID/RORORS /BK70MHMULTI/RO3/BK	240	(2) 250W MH (1) 70W MH	POLE	CITY OF BELLVILLE STANDARD FIXTURE. SEE DETAIL #1 SHEET E-4 FOR INSTALLATION. PROVIDE "IN-USE" WP RECEPTACLE COVER. PROVIDE FUSING IN BASE.
AB	STERNBERG 2-1527R/FG/CAS6-HS-LS/250MHMULTI/RO4 69251TP8/SVO/FHD/BCC	240	(2) 250W MH	POLE	CITY OF BELLVILLE STANDARD FIXTURE. SEE DETAIL #3 SHEET E-4 FOR INSTALLATION. PROVIDE "IN-USE" WP RECEPTACLE COVER. PROVIDE FUSING IN BASE.
B	STERNBERG 1-1527R/FG/CAS6-HS-LS/100MHMULTI/RO3 69207TP8/SVO/FHD/BCC/70MHMULTI/RO3/BK	240	(1) 100W MH (1) 70W MH	POLE	CITY OF BELLVILLE STANDARD FIXTURE. SEE DETAIL #2 SHEET E-4 FOR INSTALLATION. PROVIDE "IN-USE" WP RECEPTACLE COVER. PROVIDE FUSING IN BASE.
C	STERNBERG 8590/3310P5/175MHMULTI/RO5/FHC/FHD/BK	240	(1) 175W MH	POLE	CITY OF BELLVILLE STANDARD FIXTURE. SEE DETAIL #3 SHEET E-3 FOR INSTALLATION. PROVIDE FUSING IN BASE.
D	LUMIERE 6000A-MH100-240-WW-NBR-CP-TRL-EL-DSB	240	(1) 100W MH	INGROUND	INGROUND ADJUSTABLE BEAM WALL WASH FLOODLIGHT, NATURAL BRASS FINISH WITH CONCRETE POUR COLLAR, DRIVE-OVER BRAKET KET, ELECTRONIC HID BALLAST, AND TEMPERATURE REDUCTION LENS.
E	LUMIERE 6000A-MH150-240-SP-NBR-CP-TRL-EL-DSB	240	(1) 150W MH	INGROUND	INGROUND ADJUSTABLE BEAM SPOT LIGHT, NATURAL BRASS FINISH WITH CONCRETE POUR COLLAR, DRIVE-OVER BRAKET KET, ELECTRONIC HID BALLAST, AND TEMPERATURE REDUCTION LENS.

PANEL NO: SVC-1 LP1 — 10,000 AIC

VA	FUNCTION	SIZE	CKT	PH	CKT	SIZE	FUNCTION	VA
	MAIN	100A/2P	1	A	2	20A/1P	SPARE	---
			3	B	4	20A/1P	SPARE	---
---	SPARE	20A/1P	5	A	6	20A/1P	CONTACTOR CONTROL	500
---	SPARE	20A/1P	7	B	8	20A/1P	SPARE	---
---	SPACE	---	9	A	10	---	SPACE	---
---	SPACE	---	11	B	12	---	SPACE	---
---	SPACE	---	13	A	14	50A/2P	CONTACTOR	4370
---	SPACE	---	15	B	16	50A/2P	CONTACTOR	4370
2345	N.W. STREET LIGHTS	30A/2P	17	A	18	30A/2P	S.W. STREET LIGHTS	2150
2165	N.W. STREET LIGHTS	30A/2P	19	B	20	30A/2P	S.W. STREET LIGHTS	2150
---	SPACE	---	21	A	22	20A/2P	S.W. PLAZA LIGHTS	613
---	SPACE	---	23	B	24	20A/2P	S.W. PLAZA LIGHTS	613
---	SPACE	---	25	A	25	---	SPACE	---
---	SPACE	---	27	B	28	---	SPACE	---
---	SPACE	---	29	A	30	---	SPACE	---
---	SPACE	---	31	B	32	---	SPACE	---

VOLTAMPS: A — B — TOTALS: 19038 — VOLTS: 120/240 VAC, 1ø, 3W
PHASE: 9769 — 9269
MAINS: 100A MCB LOAD CENTER — POLES: 32 POSITIONS — MOUNTING: PEDESTAL

PANEL NO: SVC-4 LP4 — 10,000 AIC

VA	FUNCTION	SIZE	CKT	PH	CKT	SIZE	FUNCTION	VA
	MAIN	100A/2P	1	A	2	20A/1P	SPARE	---
			3	B	4	20A/1P	SPARE	---
---	SPARE	20A/1P	5	A	6	20A/1P	CONTACTOR CONTROL	500
---	SPARE	20A/1P	7	B	8	20A/1P	SPARE	---
---	SPACE	---	9	A	10	---	SPACE	---
---	SPACE	---	11	B	12	---	SPACE	---
---	SPACE	---	13	A	14	50A/2P	CONTACTOR	3873
---	SPACE	---	15	B	16	50A/2P	CONTACTOR	3873
2235	N.E. STREET LIGHTS	30A/2P	17	A	18	20A/2P	N.W. PLAZA LIGHTS	1138
2235	N.E. STREET LIGHTS	30A/2P	19	B	20	20A/2P	N.W. PLAZA LIGHTS	1138
888	N.E. PLAZA LIGHTS	20A/2P	21	A	22	---	SPACE	---
888	N.E. PLAZA LIGHTS	20A/2P	23	B	24	---	SPACE	---
---	SPACE	---	25	A	26	---	SPACE	---
---	SPACE	---	27	B	28	---	SPACE	---
---	SPACE	---	29	A	30	---	SPACE	---
---	SPACE	---	31	B	32	---	SPACE	---

VOLTAMPS: A — B — TOTALS: 19038 — VOLTS: 120/240 VAC, 1ø, 3W
PHASE: 9769 — 9269
MAINS: 100A MCB LOAD CENTER — POLES: 32 POSITIONS — MOUNTING: PEDESTAL

PANEL NO: SVC-7 LP7 — 10,000 AIC

VA	FUNCTION	SIZE	CKT	PH	CKT	SIZE	FUNCTION	VA
---	MAIN	100A/2P	1	A	2	20A/1P	EXISTING CLOCK	1200
---			3	B	4	20A/1P	RECEPTACLE	180
---	SPARE	20A/1P	5	A	6	20A/1P	CONTACTOR CONTROL	500
---	SPARE	20A/1P	7	B	8	20A/1P	SPARE	---
---	SPACE	---	9	A	10	---	SPACE	---
---	SPACE	---	11	B	12	---	SPACE	---
---	SPACE	---	13	A	14	50A/2P	CONTACTOR	3752
---	SPACE	---	15	B	16	50A/2P	CONTACTOR	3752
---	SPACE	---	17	A	18	30A/2P	S.E. STREET LIGHTS	2150
---	SPACE	---	19	B	20	30A/2P	S.E. STREET LIGHTS	2150
---	SPACE	---	21	A	22	30A/2P	S.E. PLAZA LIGHTS	1713
---	SPACE	---	23	B	24	30A/2P	S.E. PLAZA LIGHTS	1713
---	SPACE	---	25	A	26	---	SPACE	---
---	SPACE	---	27	B	28	---	SPACE	---
---	SPACE	---	29	A	30	---	SPACE	---
---	SPACE	---	31	B	32	---	SPACE	---

VOLTAMPS: A — B — TOTALS: 18888 — VOLTS: 120/240 VAC, 1ø, 3W
PHASE: 9204 — 7684
MAINS: 100A MCB LOAD CENTER — POLES: 32 POSITIONS — MOUNTING: PEDESTAL

Δ Revised 11-5-07

Kaskaskia Engineering Group L.L.C.
23 Public Square Suite 404
Belleville, Illinois 62220
Office: (618) 233-5977 Fax: (618) 233-5977
www.kaskaskiaeng.com
A Disadvantaged Business Enterprise

PREPARED BY:

PROFESSIONAL ENGINEERS — LICENSE NO.
ILLINOIS PROFESSIONAL SEAL — 184.005775
PROFESSIONAL ENGINEERING CORP. — 25-000208

BRiC PARTNERSHIP, LLC
CONSULTING ENGINEERS
100 EAST WASHINGTON, SUITE 220
BELLEVILLE, IL 62220
TEL 618.277.1250 FAX 618.277.5327

SEAL

Signature:

Expiration Date:

REV.	DATE	DESCRIP
1	10/25/07	REVISION #1

SHEET TITLE: ELECTRICAL SCHEDULES

PROJECT TITLE: BELLEVILLE SQUARE
CITY OF BELLEVILLE
ST. CLAIR COUNTY, ILLINOIS

DESIGNED BY: BSF	SHEET
DRAWN BY: GYK/BSF	44
CHECKED BY: BEC	E5.1
DATE OF PRELIMINARY: 09/17/2007	
DATE OF FINAL:	
SHEET NO. 13 OF 13 SHEETS	
PROJECT NUMBER 07-0941	