

FED. ROAD DIST. NO. ILLINOIS FED. AID PROJECT





INSTALLING THE LOOP WIRE:
THE NEGATIVE LEAD SHALL BE CONNECTED TO THE BLACK CONDUCTOR
OF A PAIR OF CONDUCTORS IN THE LEAD-IN CABLE AND THE POSITIVE
LEAD SHALL BE CONNECTED TO THE COLOR-CODED CONDUCTOR OF
THE CABLE PAIR.

DETECTOR LOOP WIRE INSTALLATION

DETECTOR NOTES:

- 1. THE DETECTOR LOOP SHALL BE CENTERED IN THE LANE IN WHICH IT IS SHOWN. ANY ADJUSTMENTS ARE TO BE MADE ONLY AT THE DIRECTION OF THE ENGINEER.
- 2. THE DETECTOR LOOPS SHALL CONSIST OF THE NUMBER OF TURNS AS SHOWN IN THE PLANS OR AS DIRECTED BY THE ENGINEER.
- 3. ACCEPTANCE OF THE LOOPS AS WETERED SHALL BE DETERMINED BY THE ENGINEER.
- 4. ALL DETECTOR WIRES SHALL BE WARKED WITH WATERPROOF LABELS USING THE WIRING IDENTIFICATION SHOWN ON THE PLANS. THE + AND OF EACH LOOP MUST BE USED TO IDENTIFY CURRENT FLOW. ALWAYS CONNECT THE BLACK WIRE OF EACH PAIR TO THE NEGATIVE (-) LOOP WIRE.
- 5. ALL QUADRAPOLE LOOPS SHALL BE 2-4-2 DESIGN.
- 6. THE CONTRACTOR SHALL CONTACT DISTRICT 6 OPERATIONS FOR ASSISTANCE IN DETECTOR LOOP LAYOUT AT LEAST 48 HOURS BEFORE INSTALLING DETECTOR LOOPS (Pn. = 217-558-6523)

REVISIO		ILLINOIS OFPART	MENT OF TRANSPORTATION				
NAME	DATE		•				
•		TRAF	FIC SIGNAL				
		DETECTOR	R LOOP DETAILS				
		IL 29 e	HILLTOP ROAD				
		SANGAMON COUNTY					
		SCALE: VERT.	DRAWN BY				
	+	DATE HORIZ.	CHECKED BY				

LOOP	NUMBER OF TURNS	R	EADING @	HANDHOLI	OR	$\ $	READING CONTROLLER				
DESIGNATION		CALCL	JUNCTION BOX CALCULATED METERE			Н	CALCUL	ATFD			
		μη	μη Ω		μη Ω		μη	Q	Ω μη		
WRF	4	141	0.36	•		П	174	5.26			
#LF	4	144	0.42			H	177	5.33		_	
WR <u>E</u> WLE	- 1	142 145	0,38 0,44			Н	158 161	2.72 2.79			
SRP	₹	169	0,44			H	182	2.40			
SAP	2	156	0,57			Ħ	170	2.52			
SAB	2	180	0.66			П	194	2.61			
ELT	2-4-2	357	1.05			П	379	4.26			
ELB	2	183	0.66			Ш	205	3,88			
ELE	4	143	0.40			Н	185	6.67			
ERE	4	140	0.34			Н	183	6.61			
ELF ERF	4	141	0.41 0.34			H	203 200	9 <u>.23</u> 9 <u>.</u> 17			
F141	-		015-			Ħ	200	241.			
						П					
						П					
						Н					
						H					
-						╁╂				\vdash	
						Ħ					
						Ħ					
						П					
						41				\vdash	
						Н					
		-			-	₩				-	
		-			 	╫				\vdash	
						Ħ					
						П					
						Ш					
						H					
						H					
						H					
						Ħ					
						Ħ					
						П					
						Ц					
						44					
						Н					
						Н					
						Ħ					
						П					
						П					
						Ш					
						H					
						Н					
						H					
						Ħ					
						П					
						П					
						П					
ļ						#				_	
						╫				-	
-						╫				\vdash	
						╁┼					
						Ħ					
						П					
						Д					
						44				_	
						₩					
			-	-	 	╫				 	
						₩					
						#					
						П					
						П					
						44				_	
						₩				\vdash	
		 		-	 	╫				-	
						╫					
						Ħ					
						П					
						П					
						П					
						44				_	
					 	44				<u> </u>	
		-			-	╫				-	
					l	H				\vdash	
-		-	t	-	 	++			 	_	