



19th & Richmond Ave.

LOOP:	SIZE:	MODE:	QUADRA-POLE:	DELAY:
A1,A4,A7,A2,A5,A8, A3,A6,A9, B1,B4,B7,B2,B5,B8, B3,B6,B9, D1,D3	6' X 6'	NORMAL	NO	0
A10,A11,B10,B11	6' X 6'	EXTENDED	NO	0
D2	6' X 10'	DELAY	NO	15

THE FOLLOWING CABLES SHALL BE WIRED TO COMMON AMPLIFIERS:
 (A1, A4, A7), (A2, A5, A8),
 (A3, A6, A9), (A10), (A11)
 (B1, B4, B7), (B2, B5, B8),
 (B3, B6, B9), (B10), (B11),
 (D1, D3), (D2)
 12 AMPLIFIERS PLUS 2 ADDITIONAL
 TOTAL 14 AMPLIFIERS

NUMBER OF TURNS REQUIRED
IN DETECTOR LOOPS

6 X 6		LOOP SIZE
		2 TURNS
		3 TURNS
0	545	4 TURNS
546	818	5 TURNS
819	1145	6 TURNS
1146	1527	7 TURNS
1528	1964	8 TURNS
1965	2455	9 TURNS
2456	3000	10 TURNS

THE NUMBERS IN THE TABLE REPRESENT THE LENGTH OF ELECTRIC CABLE FROM THE LOOP TO THE CABINET